

U ZIP arhivi koju ste preuzeli , pored ovog uputstva imate direktorijum «CQ-V TR4W NV» i fajl «CQV.DOM».

Ceo direktorijum CQ-V TR4W NV kopirajte u C:\Program Files\TR4W\

Fajl CQV.DOM kopirajte u C:\Program Files\TR4W\DOM\

Konfiguracioni fajl CQ Vojvodina.cfg, koji se nalazi u C:\Program Files\TR4W\ CQ-V TR4W NV
podesiti prema donjem uputstvu.

Podešavanja fajla CQ Vojvodina.CFG za TR4W program
U fajlu CQ Vojvodina.cfg treba zameniti karaktere oznacene crveno, tj. uneti sopstveni CALL .

PRIMER:

MY CALL = YT1KC

CONTEST = RSGB-IOTA

CONTEST NAME = CQ Vojvodina

BAND = 80

MY QTH =

QSO NUMBER BY BAND = false

DOMESTIC MULTIPLIER = DOMESTIC FILE

DOMESTIC FILENAME = CQV.DOM

INITIAL EXCHANGE FILENAME = sints.qth

MULT BY BAND = true

MULT BY MODE = true

PREFIX MULTIPLIER = PREFIX

QSO POINT METHOD = ONE PHONE TWO CW

[Messages]

CQ MEMORY F1=TEST \\ TEST

CQ MEMORY F3=TU

CQ MEMORY F4=@

CQ MEMORY F5=@

CQ MEMORY F6=NR?
CQ MEMORY F7=?
CQ MEMORY F8=@ AGN
CQ MEMORY F9=@ QSO B4 \ TEST
CQ MEMORY F10=:
CQ MEMORY F11=
CQ MEMORY F12=73
EX MEMORY F3=TU
EX MEMORY F4=\
EX MEMORY F5=@
EX MEMORY F6=NR?
EX MEMORY F7=?
EX MEMORY F8=@ AGN
EX MEMORY F9=
EX MEMORY F10=:
EX MEMORY F11=5NN #-1
EX MEMORY F12=73
CQ MEMORY ControlF1=CQ TEST \\ TEST
QSL MESSAGE=TU \\ TEST
QUICK QSL MESSAGE=TU \
QSO BEFORE MESSAGE=^ QSO B4 \\ TEST
CALL OK NOW MESSAGE=@
CQ MEMORY F11=5NN #-1
CQ MEMORY F2=5NN #
S&P EXCHANGE=^ 5NN #
CQ EXCHANGE=^ 5NN #
REPEAT S&P EXCHANGE=@ 5NN #

CQ CW MEMORY CONTROLF10=QTH ?
CQ CW MEMORY CONTROLF10 CAPTION=
CQ CW MEMORY CONTROLF9=OK?

CQ CW MEMORY CONTROLF9 CAPTION=

EX CW MEMORY CONTROLF7=

EX CW MEMORY CONTROLF7 CAPTION=

EX CW MEMORY CONTROLF9=OK?

EX CW MEMORY CONTROLF9 CAPTION=

EX CW MEMORY CONTROLF10=QTH?

EX CW MEMORY CONTROLF10 CAPTION=

EX CW MEMORY CONTROLF11=QRL?

EX CW MEMORY CONTROLF11 CAPTION=

QSO BEFORE CW MESSAGE=^ SRI QSO B4 \ TEST

EX CW MEMORY F4=**YT1KC**

EX CW MEMORY F4 CAPTION=

CQ CW MEMORY F4=**YT1KC**

CQ CW MEMORY F4 CAPTION=

CQ CW MEMORY F5=@

CQ CW MEMORY F5 CAPTION=

EX CW MEMORY F5=@

EX CW MEMORY F5 CAPTION=

CQ CW MEMORY F1=TEST \\ TEST

CQ CW MEMORY F1 CAPTION=

EX CW MEMORY F12=73

EX CW MEMORY F12 CAPTION=73

CQ CW MEMORY F12=73

CQ CW MEMORY F12 CAPTION=73

CQ CW MEMORY F11=5NN #-1

CQ CW MEMORY F11 CAPTION=

CQ CW MEMORY F2=5NN #

CQ CW MEMORY F2 CAPTION=

EX CW MEMORY F11=5NN #-1

EX CW MEMORY F11 CAPTION=

[Commands]

LEADING ZEROS=3